

*optional current shunt for DM-9131*

# **200 AMP CURRENT SHUNT**

**Model : LS-04**

*ISO-9001, CE, IEC1010*

---



---

**LUTRON ELECTRONIC**

*The Art of Measurement*

# 200 AMP CURRENT SHUNT

## Model : LS-04

*Optional current shunt for DM-9131*

### SPECIFICATIONS

Range	0 - 200 Amps
Output	1 DC mV per 1 DC A
Accuracy	$\pm ( 4 \% + 1.5 \text{ mV } )$ <i>@ 23 <math>\pm</math> 5°C</i>
Application	* To cooperate with the " Car Tester " DM-9131, set the meter's range to DC 200 mV range, then the display reading will get the DCA value directly. For example, if the display reading value is 150.0 mV, then the exact DCA measurement value will be 150.0 DCA. * To measure all kind car electric DC current.
Size	160 x 50 x 26 mm.
Weight	200 g.
Accessories Included	Operational manual..... 1 PC.

\* Appearance and specifications listed in this brochure are subject to change without notice.

1805-LS04